

型 S8VS 开关电源

CHN 使用说明书

感谢您购买了S8VS的产品。此说明书内记载了S8VS使用时的功能、性能及使用方法。...

OMRON Corporation
©All Rights Reserved

警告标识的含义

注意 若操作不当的话有可能发生轻度伤害或设备损坏的危险。

警告标识

Table with 2 columns: Warning symbol and description. Includes symbols for fire, electric shock, and high voltage.

CHN 安装使用要求

- (1) 安装/存储环境: 请在环境温度-25~+65°C, 相对湿度为25~90%的条件下储藏本产品。
(2) 设置/配线: 请连接地线, 确保接地端子处于安全使用状态。

Table with 3 columns: Terminal, Model, Recommended wire gauge. Lists input and output terminals for various models.

- 4. 紧固端子时, 请不要用100N以上的力去按压端子台。
5. 通电前, 请确定加工时覆盖在产品上面的薄膜已经被取下。

CHN 使用时的注意事项

以下使用用途时, 请与本公司营业人员商谈。认真确认规格书的同时, 需确保额定·性能上保有余量。...

MODEL S8VS SWITCHING POWER SUPPLY

EN INSTRUCTION MANUAL

Thank you for purchasing the S8VS. This Instruction Manual describes the functions, performance, and application methods required to use the S8VS.

OMRON Corporation
©All Rights Reserved

Key to Warning Symbols

CAUTION Indicates a potentially hazardous situation which, if not avoided, may result in minor or moderate injury or in property damage.

Warning Symbols

Table with 2 columns: Warning symbol and description. Includes symbols for minor electric shock, minor burns, and minor injury.

EN Precautions for Safe Use

- (1) Installing/Storage Environment: Store the product with ambient temperature -25 to +65°C, and relative humidity 25 to 90%.
(2) Arrangement/Wiring: Connect the ground completely. A protective earthing terminal stipulated in safety standards is used.


Table with 3 columns: Terminal, Model, Recommended Wire Type. Lists alarm output and ground terminal specifications.

- 4. Do not apply more than 75N force to the terminal block when tightening it.
5. Be sure to remove the sheet covering the product for machining before power-on.

EN Suitability for Use

OMRON shall not be responsible for conformity with any standards, codes, or regulations that apply to the combination of the products in the customer's application or use of the product.


Fig.1 各部位名称/Nomenclature



CHN 各部位名称



EN Nomenclature




CHN 正确的使用方法

- 安装: 标准安装, 向上安装, 其他安装。
■安装空间: 为了保持安装产品的长期可靠性, 请注意散热。
■降额曲线: 侧面安装型(形S82Y-VS10S)右侧安装时(-24024□□□□除外)。

EN Precautions for Correct Use

- Mounting: Standard Mounting, Horizontal Mounting, Others Mounting.
■Mounting Space: Install the power supply so that the air flow circulates around the power supply.
■Input Voltage Tolerance: 100 to 240 VAC (allowable range: 85 to 264 VAC, 80 to 370 VDC).

- Overload Protection: The load and the power supply are automatically protected from overcurrent damage by this function.
■Overvoltage Protection: This power supply automatically protects itself and the load from overvoltage.
■Alarm Output: (Only for S8VS-□□□□24A□□□□□□□□□□, except for -06024A/B□□□□□□□□□□).



Contact address: OMRON Corporation, Shikoji Horikawa, Shimogyo-ku, Kyoto, 600-8530 Japan.

技术咨询: 800免费技术咨询电话: 800-820-4535 (仅限于中国大陆).

制造单位: 欧姆龙(上海)有限公司, 地址: 上海市浦东新区金桥出口加工区金吉路789号.

联系方式: 欧姆龙亚洲有限公司(台北), 欧姆龙欧洲有限公司(香港), 欧姆龙欧洲有限公司(台湾).

型 S8VS 开关电源

CHN 操作说明

感谢购买使用欧姆龙产品。为了安全、正确使用本产品，使用前请认真阅读、理解《操作说明》，阅读后请放在身边，便于需要时使用。

阅读时请结合《S8VS使用说明书》。

OMRON Corporation
©All Rights Reserved

更换时间提示功能（显示·输出） （仅限S8VS-□□□24A□□□）

Fig.3

■所谓更换时间提示功能
电源内置有电解电容。
电解电容从生产成品（※2）开始，其电解液就会逐渐渗透密封橡胶，随时间增长渐渐挥发，从而产生以静电容量减少（※3）为主的特性恶化。
由于电解电容特性恶化，电源经过一段时间后便不能发挥出预期的性能。更换时间提示功能可以显示随电容电解特性恶化，电源还能发挥预期性能的预计时间。另外，达到设定值时，会提示并输出警报。
可利用此功能来预计电源本体的更换时间。

注：
更换时间提示功能只提示由于电解电容恶化引起的电源性能不能发挥的预计时间，不包括由其他原因引起的故障。

■动作原理
电解电容的恶化速度与周围温度密切相关。（一般为10°C时候的2倍、遵照阿伦尼乌斯法则）。仅限
S8VS-□□□24A□□□通过监测通电状态下电源的内部温度，根据工作时间与内部温度计算出电解电容的恶化量，然后通过显示与输出提示更换时间。

- 注：
1. 由于电子产品的耐久性，无论更换时间提示与否，在购买15年后请进行更换。
2. 更换时间会随着使用条件发生增减变化。请定期进行确认。
3. 由于更换时间的增减变化，有时输出会ON、OFF反复。
4. 交流输入ON/OFF的反复应用，有时会影响到更换时间提示功能的精度。

■显示与输出
购买时显示为FUL（※4）。由于使用，随着电解电容恶化，显示变为HLF（※5）。到距离更换不足2年时自动变为数字显示（※6），并随着工作时间的增加逐步减少为1.5、1.0、0.5、0.0（年）。
当更换时间提示的设定值大于2年时，一旦距离更换剩余时间低于设定值，自动变为数值显示。
剩余时间少于设定值L（0~5.0年间可任意设定）时，警报（RG2）与剩余时间交替显示。
S8VS-□□□24A□□□（-06024A-□除外）为晶体管（⑫Yrs）输出，提示更换时间。（到达更换时间时OFF；⑫~⑬非导通）



- 注：
1. 剩余时间不包括非通电时间。
2. 工作时间累计达到约1个月前，由于推断恶化速度，显示固定为FUL，输出保持ON（⑫~⑬导通）。

■定期检查（S8VS-□□□24A□□□/□□□□□，-06024A/□□□除外）
一般使用条件下，本产品到达提示更换时间需要几年到十几年（S8VS-□□□24A□□□□□）。另外，累计工作时间根据设定值有时会与更换时间提示的年数相同。（S8VS-□□□24B□□□□□）长期使用，请定期按照以下步骤对更换时间提示输出（⑫Yrs）或累计工作时间输出（⑫kh）是否正常工作进行确认。

1. 设为运行模式。
 2. 请确认输出（⑫Yrs/kh）为ON（⑫~⑬导通）。
 3. 运行模式下，∨（⑩）和⊞（⑧）同时连续按3秒以上。主显示部（⑥）变为RG2
- RG2显示中输出（⑫ Yrs/kh）如果为OFF（⑫~⑬ 非导通）则正常。
4. 松开按键即返回通常状态。
- 注：定期检查中，直流输出不为OFF。

MODEL S8VS SWITCHING POWER SUPPLY

EN Operation Manual

Thank you for purchasing this OMRON product. This manual primarily describes precautions required in operating the power supply. Before operating the product, read this manual thoroughly to acquire sufficient knowledge of the product to use it safely and correctly. Keep this manual close at hand and use for reference during operation. Read the S8VS Instruction Manual together with this manual without fail.

OMRON Corporation
©All Rights Reserved

Maintenance Forecast Monitor Function (Indication and output) (Only for S8VS-□□□24A□□□)

Fig.3

■What is "Maintenance Forecast Monitor Function" ?
The power supply unit is equipped with electrolytic capacitors. The electrolyte inside the electrolytic capacitor penetrates the sealing rubber and evaporates as time passes since it is manufactured, which causes deterioration of characteristics such as decreasing the capacitance (3), etc.
Due to this deterioration of the characteristics of the electrolytic capacitor, the power supply unit decreases its performance as time passes. The maintenance forecast monitor function shows an approximate period left for maintenance of the power supply unit due to deterioration of electrolytic capacitors. When the period left for maintenance that the power supply forecasts reaches the set value, an alarm is indicated and an output signal is triggered.
Use this function to know the approximate replacement timing of the power supply unit.
Note:
THE MAINTENANCE FORECAST MONITOR FUNCTION INDICATES AN APPROXIMATE PERIOD LEFT FOR MAINTENANCE, BASED ON DETERIORATION OF THE ELECTROLYTIC CAPACITOR. IT DOES NOT PREDICT FAILURES CAUSED BY OTHER REASONS.

■Principle of operation
The deterioration speed of the electrolytic capacitor varies considerably according to the ambient temperature. (Generally the speed follows "Rule of Two for every 10°C"; for every 10°C increase in temperature the rate of degradation doubles according to Arrhenius's equation.) The S8VS-□□□24A□□□ only monitors the temperature inside the power supply, and calculates the amount of deterioration according to the running hours and inside temperature. Judging by this amount of deterioration, the power supply will give the alarm indication and output when the period left for maintenance reaches the set value.


- Notes:
1. Due to degradation of internal electronic parts, replace the power supply at least once every 15 years even if indication and output of maintenance forecast monitor are not issued.
 2. The maintenance forecast is accelerated or decelerated according to operating conditions. Periodically check indication.
 3. The output may turn ON and OFF alternately according to the acceleration or deceleration of Maintenance forecast.
 4. The accuracy of Maintenance forecast monitor may become worse in the application having frequent ON/OFF for AC power.

■Indication and Output
When the product is purchased, "FUL" (※4) will be indicated. As electrolytic capacitors deteriorate, indication changes to "HLF" (※5). After the remaining time to maintenance is reduced to two years, indication automatically changes to a value (※6), which decreases from "1.5" to "1.0" to "0.5" to "0.0" (year) as the running hours increase.
If the maintenance forecast monitor setting is set to a value larger than two years, value indication automatically begins after the remaining time to maintenance is reduced to the set years.
If the remaining time becomes smaller than setting L (which can be set arbitrarily between 0 and 5.0 years), an alarm (RG2) and the remaining time are indicated alternately.
With the S8VS-□□□24A□□□(except for-06024A-□), an output is given to an external device from a transistor (⑫ Yrs) to notify of the replacement timing, together with indication. (The output is turned off after the replacement timing is reached; with no continuity across ⑫ and ⑬.)




1. The remaining time to maintenance is based on continuous operation, not including the time when the power supply is turned off, and so may take longer to reach than the actual time indicated.
 2. Until the power supply has been turned for about one month in total, indication is fixed at "FUL" to estimate the extent of deterioration, while the output remains turned on (with continuity across ⑫ and ⑬).
- PERIODIC CHECK (S8VS-□□□24A□□□/□□□□□, except for-06024A/□□□)
- It may take from several years to several tens of years under general operating conditions for the power supply to give the maintenance forecast monitor alarm (S8VS-□□□24A□□□□□). The total run time monitor (S8VS-□□□24B□□□□□) may be a similar number of years to the maintenance forecast monitor according to some setting. During operation over an extended period of time, periodically check if the maintenance forecast monitor output (⑫ Yrs) or total run time monitor output (⑫ kh) is correctly functioning by the following procedure.
1. Select the operation mode.
 2. Check that the output (⑫ Yrs / kh) is turned on (with continuity across ⑫ and ⑬).
 3. In the operation mode, press and hold the ∨ (⑩) and ⊞ (⑧) keys simultaneously for at least three seconds. The main display (⑥) changes to "RG2." An inactive output (⑫ Yrs / kh) (no continuity across ⑫ and ⑬) in the "RG2" indication indicates the correct function.
 4. Release keys to return to the regular state.
- Note: DC output stays ON while the periodical check.

Fig.1 各部位名称/Nomenclature




S8VS-06024A/B-□ S8VS-□□□24A□□□/□□□□□(-06024A/□□□除外)
轮廓尺寸图适用于S8VS-09024A。
S8VS-□□□24A□□□/□□□□□(except for-06024A/□□□)

Fig.2 电压不足检测机能/Undervoltage alarm function



注：产品通电约3秒后动作开始/
Note: Operation begins after about 3 seconds since the AC power is supplied.


Fig.3




操作方法和功能

■部品名称与功能

名称	功能
⑥主显示部	显示测量值或设定值。
V	输出电压显示中连续发光。不足电压检出设定中闪烁。
A	输出电流显示中连续发光。
⑦动作显示部	Apk 峰值电流显示中连续发光。
Yrs	显示更换时间提示中连续发光。更换时间提示值设定中闪烁（S8VS-□□□24A□□□）
kh	累计工作时间显示中连续发光。累计工作时间值设定中闪烁（S8VS-□□□24B□□□/□□□□□）
⑧模式键	切换显示参数时或设定峰值电流值时使用
⑨上调键	转为设定模式时或调高设定值时使用
⑩下调键	转为设定模式时或调低设定值时使用




注：
S8VS-06024A/B-□没有设定模式



注：
出厂时以输出电压显示状态启动。以后以输入断路前的状态启动。

■设置模式（S8VS-06024A/B-□除外） 显示电源的各种参数设定



注：
1. ∨（⑨）或∧（⑩）连续按2秒以上，设定值可以快进。
2. S8VS-06024A/B-□没有设置模式。各种参数为出厂时的固定值。

■输出电压·电流显示功能
监视、显示电源的输出电压和电流。

■峰值电流显示功能
记忆、显示输出电流的最大值。与显示模式无关，输出电流的最大值一直保持更新。另外，即使输入断路，峰值电流也会保持。

■峰电流值重置
3秒以上 2秒以后
运行模式 重置 峰电流测定开始

注：
峰电流不能在设置模式下重置。

■自我诊断功能

主显示部	内容	输出状态	复位方法	复位后的设定值
FUL	检出输出电压或输出电流中有干扰	没有变化	自动复位	没有变化
HLF	本体异常过热	⑩OFF	自动复位	没有变化
1.5	不足电压设定值记忆异常	⑩OFF	自动复位	没有变化
1.0	更换时间提示或累计工作时间报警设定值的记忆异常	⑩OFF	∨（⑨）或∧（⑩）按3秒，确认该处的设定值，返回出厂设定。	出厂设定值或设置模式下再次设定的值
0.5	其他记忆异常	⑩⑫OFF	请重新输入电源。仍不复时，请与购买店联系。	没有变化

- 注：
1. ---, EB* 发生的原因，主要考虑为外部有干扰侵入。
2. HLF 发生的原因，主要考虑为超过降额曲线条件下的使用、通风异常、安装方向错误等。
3. HLF 状态持续3小时以上时，更换时间提示功能无效。即使过热状态解除，更换时间提示显示仍持续显示为Hof Yrs输出（⑫）持续为OFF（⑫~⑬非导通）。即使能够正常直流输出，由于内部部品可能已经恶化，请更换本体。
4. 只有S8VS-□□□24A□□□有Hof的检出功能。

Operation and Function


■Name and Function of Each Part

Name	Function
⑥/Main display	Indicates the measurement or set value.
V	Lights up when the output voltage is indicated. Blinks during setup of undervoltage alarm value.
A	Lights up during indication of output current.
Apk	Lights up during indication of peak hold current.
⑦ Operation indicator	Lights up during indication of maintenance forecast monitor. Blinks during setup of maintenance forecast monitor setting. (S8VS-□□□24A□□□)
Yrs	Lights up during indication of total run time monitor. Blinks during setup of total run time monitor. (S8VS-□□□24B□□□/□□□□□)
kh	Lights up during indication of total run time monitor. Blinks during setup of total run time monitor. (S8VS-□□□24B□□□/□□□□□)
⑧ Mode key	Use the mode key to change the indicated parameter or reset the peak hold current value.
⑨ Up key	Use the up key to change to the setting mode or to increase the set value.
⑩ Down key	Use the down key to change to the setting mode or to decrease the set value.

■Mode Change
Power-ON
Model indication
Press and hold ∨ or ∧ for three seconds or more.
Operation mode
Setting mode
Press and hold ∨ or ∧ for three seconds or more.
Or no key operation for 30 seconds or more.

注：
No setting mode is provided for the S8VS-06024A/B-□.

■Operation Mode
Various states of the power supply unit are indicated.



注：
The output voltage will be displayed when the power supply is first turned on after it is received from the factory. Thereafter, the output voltage will be indicated in the same display when shutting down.

■Setting Mode (except for S8VS-06024A/B-□)
Set various parameters of the power supply unit.

■Output Voltage and Current Indication Function

The output voltage and current of the power supply unit are monitored and indicated.
Note: Operation begins after about 3 seconds since the AC power is supplied.

■Peak Hold Current Reset
3 seconds or more 2 seconds
Operation mode Reset Peak hold current value measurement starts

注：
The peak hold current value is not reset in the setting mode.

■Undervoltage alarm Function (Indication and output)
When output voltage drop is detected, an alarm (RG1) and lowest output voltage value are indicated alternately. The preset value of detection voltage can be changed in the setting mode. (S8VS-06024A/B-□). The value of detection voltages is fixed at 20.0V.

■Total run time monitor Indication and Alarm Output (S8VS-□□□24B□□□/□□□□□)
The cumulative running hours of the power supply unit are monitored as total run time. When the total run time reaches the predetermined alarm set value, an alarm (RG2) and the total run time monitor are indicated alternately with an output issued from the transistor (⑫ kh) to an external device. (The output is turned off when the total run time reaches the alarm set value; with no continuity across ⑫ and ⑬). The alarm set value can be changed in the setting mode.

注：
1. The total run time cannot be reset. To reset the alarm, increase the alarm set value beyond the value indicated as total run time.
2. The alarm function (setting, indication, and output) is not provided for S8VS-06024A/B-□.
3. The alarm output function is not provided for S8VS-□□□24B□□□.

■Further, the alarm is output from the transistor (⑫ DC LOW) to an external device with the S8VS-□□□24A□□□/□□□□□ (except for-06024A/B-□). (Upon output voltage alarm: OFF; with no continuity across ⑫ and ⑬.)

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

Further, the alarm is output from the transistor (⑫ DC LOW) to an external device with the S8VS-□□□24A□□□/□□□□□ (except for-06024A/B-□). (Upon output voltage alarm: OFF; with no continuity across ⑫ and ⑬.)

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued

注：
In the case that the output voltage drops below the set value (19V) and an alarm is issued